

25-Watt TRIAC LED Power Supply

Phase-dimming transformer for interior applications

Commercial Grade




This high-quality 25W TRIAC-dimmable LED transformer is available in a choice of 12v and 24v versions. Offering industry-standard phase-cut functionality, it enables dimming of white or single-colour LED strips using a standard household dimmer-switch. (Aurora's AU-DSP400X dimmer module and Varilight's V-Pro series are recommended.)

This LED transformer is ideal for small rooms and feature lighting applications. It can power up to 25 watts of LED tape, with no minimum load. The transformer has a slimline design, making it easy to install unobtrusively, and it is compatible with lighting control brands such as Lutron, Rako and Crestron.

Input voltage 180-240v AC. Output voltage 12v or 24v (2 separate transformer models). This item is RoHS compliant and conforms to all UK safety standards.

wiring / connections

25w TRIAC Mains-Dimmable Transformer



quick spec sheet

Product code: TR-25-12 / TR-25-24

Physical construction

Colour White
Materials Plastic
IP Rating IP20
Length 155 mm
Width 54 mm
Depth 21 mm

Electrical

Input voltage 180V ~ 240V Output voltage 12V or 24V

Output current 2.08A (12V) or 1.04A (24V)

Output wattage 25W



https://www.instyleled.co.uk/triac-25w-dimmable-transformer/

tel: 0116 2799 083 email: sales@instyleled.co.uk www.instyleled.co.uk